



### 3 - Designation



UT.C. 1921



**MR V 742 U O 4 A - F0 112M 4 265.460 B5 / 148**

MOTOR MOUNTING POSITION (ch. 2b and 9): ...

GEARMOTOR OUTPUT SPEED [rpm]

VOLTAGE [V]:

**265.460**

Y460 V - 60 Hz

NUMBER OF POLES:

**4, 6**

MOTOR SIZE:

**63A ... 132MB**

MOTOR:

(HF)

**F0**

...

asynchronous three-phase  
**(omitted from designation)**

with d.c. brake

(see UT.D 162)

DESIGN:

**A**

MODEL:

**4**

SHAFT POSITION:

**O**

right angle

MOUNTING:

**U**

universal

SIZE:

**118 ... 742**

GEAR STAGE:

**V**

worm gear pair

MACHINE:

**MR**

gearmotor

In case of:

**mounting position<sup>1)</sup> differing from B3** (B3 and B8 for sizes  $\leq 535$ ; see ch. 4):

complete designation stating «**mounting position ...**»

MR V 430 UO4A - 80A 4 265.460 B5/36,5

**mounting position V5;**

**terminal box position differing from 0** (see ch. 4):

complete designation stating «**terminal box position ...**»

MR V 430 UO4A - 80A 4 265.460 B5/36,5

**terminal box position 2;**

**brake motor:**

insert the letters **F0** before motor size

MR V 430 UO4A - **F0** 80A 4 265.460 B5/36,5.

**motor supplied by the Buyer<sup>2)</sup>:**

omit voltage, and add «**motor supplied by us**»

MR V 430 UO4A - 80A 4 ... B5/36,5

**motor supplied by us.**

**gearmotor without motor:**

omit voltage, and add «**without motor**»

MR V 430 UO4A - 80A 4 ... B5/36,5

**without motor.**

1) To simplify, the designation of mounting position (see ch. 4) is referred to foot mounting only, even if gearmotors are in universal mounting (e.g.: B14 flange mounting and derivatives; B5 flange mounting and derivatives, see ch. 13).

2) The motor supplied by the Buyer must be with mating surfaces machined under «standard» rating (IEC 72-1) at least and is to be sent carriage and expenses paid to our factory for fitting to the gear reducer.